



Outdoor Recreation



Speaker
(11W)

13 Times



Camera
(16Wh)

9.4 Times



Drone
(60Wh)

2.6 Times



Car Fridge
(60W)

2.6-5.2 Hours



Projector
(65W)

2.4-4 Hours



Home Backup



Light
(10W)

15.1 Hours



Fan
(40W)

3.7 Hours



CPAP
(40W)

3.7-7.4 Hours



Refrigerator
(120W)

1.5-3 Hours



Washer
(500W)

0.3 Hours

*The data above is for reference only.



EcoFlow was founded in 2017 with a mission is to empower people and communities through portable, clean, reliable power for lasting impact by dethroning the traditional gas generator and reinventing the way the world accesses energy.

We leverages our technology and experience to build products that are thoughtful in design, creating industry-first, smart and powerful energy storage products, and strive to reinvent the way people everywhere access power.

EcoFlow Technology Ltd.

✉ Email: sales@ecoflow.com

🌐 Website: <https://ecoflow.com/>



ECOFLOW RIVER MINI

Power at Hand



RIVER mini



RIVER mini is designed to become an “Grab and Go” power station. It is lightweight at 6.3lbs and easy to carry, so it can make you feel home at outdoor, enjoy the Anywhere AC Outlets anytime at anywhere.

0-80% in 1 hour

Get back at it faster with EcoFlow's patented X-Stream technology which delivers one of the fastest recharging rates on the market. Using a built-in smart inverter, RIVER mini can recharge from 0-80% in as quickly as 1 hour and to full in 1 hours.

Outlets when you need them

They're wall outlets you can literally hold in your hand. RIVER mini also has a version with wireless charging and a 100W USB-C output port, so it's ready to power the latest tech. You can take it with you because it's more than just a pretty face - its ergonomic design is made to be picked up and go anywhere.

Go bigger with X-Boost

Take on more watts with X-Boost enabled. When you need more watts than RIVER mini can output, X-Boost provides a fix that accommodates devices totaling up to 600 watts. Power big things from a tiny portable power station.

Specification

RIVER mini



General

Model Name	RIVER mini	RIVER mini (wireless)
Capacity	210Wh	210Wh

Output

AC Output(x6)	300W total (Surge 600W)	300W total (Surge 600W)
Max Device(s) Power Supported by X-Boost	600W	600W
USB-A Output (x2)	5V, 2.4A, 12W Max	
USB-C Output(x2)	N/A	5/9/12/15/20V, 5A, 100W Max
Car Power Output(x1)	12.6V, 10A, 126W Max	
Wireless Output	N/A	15W

Input

AC Charging	300W Max
Solar Charging	100W Max
Car Charging	Supports 12V/24V Battery, 8A Max

Battery

Battery Chemistry	NCM
Cycle Life	500 cycles to 80%+ capacity
Shelf Life	1 year

Other

Connectivity	Wi-Fi supported
Dimension	9.8 x 5.5 x 5.2in / 24.9 x 14 x 13.3cm
Weight	Approx. 6.3lbs / 2.85kg

Charging Time



AC Wall Outlet
1.5 Hours
(300W)



Gas Generator**
1.5 Hours
(300W)



Solar Panel
2-4 Hours
(1x160W Solar Panel)



Car Charger
2.5-3.5 Hours
(100W)



Solar Panel Recommendations

Solar Panels	Recharge Time
110W Solar Panel	1 Set: 2.6-5.2 hrs <i>Recommended when portability matters</i>
160W Solar Panel	1 Set: 2-4 hrs <i>Recommended when quality matters</i>

*The data above is for reference only.

**The rated output power of the gas generator should be higher than the power station max AC input power.